

YN360 III
YN360 III PRO
Pro LED Video Light
User Manual



Product Specification

***5600K color temperature YN360 III**

Light Source	360 LED lamp beads and 60 RGB SMD lamps		
Color Temperature	5600K and RGB full color		
Output power	21.6W and 10.8W	Control distance	<15M
Average Service Life	50000H	Luminance Angle	55°and 110°
Weight	805G		
Compatible batteries	One NP-F series lithium batteries		
External power source	12V2A DC power supply		
Size	583*48*24mm		
Light Intensity (Full Power)	Distance	5600K	RGB full color
		0.3M	10830lux 1810Lux
	0.5M	6230lux	990Lux
		1M	1970lux

Contents: Video light (1), User Manual (1), CT Filters (1), Storage Bag(1), Sling(1), Remote Controller(1).
Note: Please contact your dealer if anything missing.

YN360 III
***3200K、5600K color temperature**

Light Source	360 LED lamp beads and 60 RGB SMD lamps			
Color Temperature	3200K、5600K and RGB full color			
Output power	21.6W and 10.8W	Control distance	<15M	
Average Service Life	50000H	Luminance Angle	55°and 110°	
Weight	805G			
Compatible batteries	One NP-F series lithium batteries			
External power source	12V2A DC power supply			
Size	583*48*24mm			
Light Intensity (Full Power)	Distance	3200K	5600K	RGB full color
		0.3M	10460lux 5720Lux	1810Lux
	0.5M	5960lux 3080Lux	3220Lux	930Lux
		1M	1997Lux	1074Lux

Contents: Video light (1), User Manual (1), CT Filters (1), Storage Bag(1), Sling(1), Remote Controller(1).
Note: Please contact your dealer if anything missing.

***5600K color temperature YN360 III PRO**

Light Source	360 LED lamp beads and 60 RGB SMD lamps		
Color Temperature	5600K and RGB full color		
Output power	21.6W and 20W	Control distance	<15M
Average Service Life	50000H	Luminance Angle	55°and 110°
Weight	805G		
Compatible batteries	One NP-F series lithium batteries		
External power source	12V2A DC power supply		
Size	583*48*24mm		
Light Intensity (Full Power)	Distance	5600K	RGB full color
		0.3M	10830lux 5430Lux
	0.5M	6230lux	2590Lux
		1M	1970lux





Contents: Video light (1), User Manual (1), CT Filters (1), Storage Bag(1), Sling(1), Remote Controller(1).
Note: Please contact your dealer if anything missing.

YN360 III PRO
***3200K、5600K color temperature**

Light Source	360 LED lamp beads and 60 RGB SMD lamps			
Color Temperature	3200K、5600K and RGB full color			
Output power	21.6W and 20W	Control distance	<15M	
Average Service Life	50000H	Luminance Angle	55°and 110°	
Weight	805G			
Compatible batteries	One NP-F series lithium batteries			
External power source	12V2A DC power supply			
Size	583*48*24mm			
Light Intensity (Full Power)	Distance	3200K	5600K	RGB full color
		0.3M	10460lux 5730Lux	5430Lux
	0.5M	5960lux 3080Lux	3220Lux	2590Lux
		1M	1997Lux 930Lux	1074Lux


Contents: Video light (1), User Manual (1), CT Filters (1), Storage Bag(1), Sling(1), Remote Controller(1).
Note: Please contact your dealer if anything missing.

Product Structure




Installation and fixed


1. Battery Installation
When installing the lithium battery, please put the battery into the slot in the direction of the arrow.
Note: NP-F series battery is applicable, please remove the battery when not in use.




b. When removing the lithium batteries, please press the battery lock and then take out the lithium batteries.




2. External power supply
It is recommended to use YONGNUO power adapter with YN360 III to obtain lasting service time. When using external power supply, the video light will stop the battery power supply automatically and will not get the battery charged. The external power supply interface outside is negative and the interface inside is positive. The input voltage is 12V and the electric current is 2A. Note: If YN360 III defective when it is used with power adapter of other brands, YN360 III will no longer be guaranteed for repair.



3. Put the remote control into the video light card slot to use.
When the remote-controller is not equipped with batteries, insert the remote-controller into the video card slot, you can use it when the remote control iron plate and the camera light magnet absorbed together. If remotely control the video light needed, install a CR2032 battery to the remote control.




4. Fasten video light as follow as needed:
Fasten the video light to the tripod directly.




Method Application


1 StartUp & Shutdown Button
Install the batteries or insert the DC power supply, and then press the power switch, the LED video light lights up. Put the remote controller into the LED video light and use it to adjust the brightness.




2. Power test
Insert the remote control into the video light card slot, the remote control displays the battery power for the video light. The battery power is 41% to 60% as shown below.




3. Coarse/Fine adjusting Switch Button
Fine/Coarse Tune Mode Press fine/coarse tune button on the remote controller to switch the tune mode. When the tune mode is switched to coarse tune mode, the adjusting unit of the brightness is 10%; when it's fine tune mode, the adjusting unit is 1%.
Note: Press and hold the 2 second coarse/fine button to lock the touch screen to avoid mistake touch; long press again to unlock.





4. Switch color temperature mode
Press the left and right buttons of remote control to switch the color temperature mode.



5. Channel switch button
A. Put the remote controller into the card slot of the video light, short press [CH] button on the controller, and the video light and the controller synchronously CH=, the controller will be switched to the channel needed. When you take the controller off, the channel of the video light and the channel of the controller is consistent.
B. For example, if the channel of the controller is switched to channel H2, the channel of the video light is CH2; when you take the controller off, the channel of the video light is as well CH2. To switch the channel of the video light, the remote controller should be inserted to the card slot of the video light.
C. If you possess several YN360 III, you can group control the brightness and switches; the groups at most is 8 groups. (The LCD screen of the remote control can display the number of CH1-8; each number corresponds to the corresponding channel, you can change the channel through the CH button.)



6. Color Temperature Filters
This product comes with a color temperature plate, take the color temperature film out from the back of the product and placed it in the front of the photographic lamp face, when it sucked by the top magnet and stick into the color temperature card slot, it ready to use.
Note: When using the video light for a long time, please remove the color temperature plate at the position of the heat dissipation hole to ensure the heat dissipation effect of the video light.



7. Mobile APP Remote Control
The product supports mobile remote control, the APP can be downloaded from the YONGNUO official website or download through scanning the two-dimension code on the gift box. Mobile phone APP will be updated continuously. Please pay attention to YONGNUO official website for latest version of APP to get better remote control experience.

8. Special Scene Supplementary Lighting Mode
1. Long press CH button for 2 seconds to enter special scene mode, F0 displays.
2. Short press CH button to switch F0-F9 (10 scenes) or left right button to switch 10 different scenes.
3. Short press coarse/fine tuning switch button to pause or start the special scene supplementary lighting.
4. Long press CH button to exit or power off and exit.

F0. Simulates lightning
F1. Simulates movie screen reflect light
F2. Simulates candlelight
F3. Simulates sunrise
F4. Simulates firework
F5. Rapid cycle among red, green, blue
F6. Slow cycle among red, green, blue
F7. Simulates police car light
F8. Simulates ambulance light
F9. Simulates fire fighting truck light

Failure Analysis and Troubleshooting

When using this product, you may encounter the following problems.

Description	Cause	Troubleshooting
No reaction after power on	Low Battery	Install new batteries or connect external power supply
	Damaged circuit board	Depot repair
Inadequate or low luminance at the greatest luminous intensity	Low battery	Install new batteries or re-charge the batteries
Inaccurate battery capacity test; low battery in high luminance and full battery in low luminance.		The battery capacity indicates the length of time available for the use in the current luminance. Higher luminance required more power and the length of time available for use will be shortened, so the battery capacity shown gets lower
The mobile phone could not remote control the video light.	Too far away	The remote control distance is within 15 meters
When press the remote control button, the light responds, the RGB touch adjustment, the light does not respond.	Remote controller has a low battery	Replace the remote controller with a new battery

The functions in this manual are based on the test conditions our company. Further notice will not be given if the design and specifications change.

Function Introduction

- YN360 III is YONGNUO brand new LED video light which brings you a more powerful fill light brightness and more wider fill light range, with easier RGB mode adjustment to meet your various fill light needs.
- YN360 III uses a combination of 360 high-definition lamp beads and 60 RGB full-color patch lights.
- The YN360 III is equipped with a proprietary multi-channel wireless remote control that easily adjusts the RGB mode via the remote control touch screen, making RGB mode adjustment easier. At the same time, it supports the frequency division control of 8 groups of video lights.
- YN360 III supports mobile phone APP to control the LED video light, reads the brightness and group channel of the current LED video light, can control the switch and brightness of 8 groups of video lights separately, and easily complete the photography needs.
- YN360 III supports dual power input, supports NP-F series battery and external DC power supply, to meet the needs of your various environments.
- YN360 III adopts YONGNUO proprietary LED constant-current drive technology, will not appear ripples or stroboscopic phenomena during the shooting.

precautions

- This product should be used under the ventilated environment. Please make sure the heat emission hole won't be blocked when you are using this spec-light.
- Do not disassemble the product, maintenance or repair of this product should be carried through by technical maintenance personnel of our company or technical maintenance personnel authorized.
- When the equipment is running, do not look into the light directly and closely.
- Do not use this product in flammable and explosive place, or where it can be exposed to moisture.
- Please keep this product away from the children.